

# Multi-User Flexible Coordinated Beamforming using Lattice Reduction for Massive MIMO Systems

Keke Zu<sup>1</sup>, Bin Song<sup>1</sup>, Martin Haardt<sup>1</sup>, and Rodrigo C. de Lamare<sup>2</sup>

1 Communications Research Laboratory, Ilmenau University of Technology  
PO Box 100565, D-98684 Ilmenau, Germany

2 Dept. of Electronics / CETUC, University of York / PUC-Rio  
York YO10 5DD, U.K./ Marquêde S.Vicente, 225 Gávea, Rio de Janeiro, Brazil

Emails: zukeke@gmail.com, {bin.song, martin.haardt}@tu-ilmenau.de, rodrigo.delamare@york.ac.uk

**Abstract**—The application of precoding algorithms in multi-user massive multiple-input multiple-output (MU-Massive-MIMO) systems is restricted by the dimensionality constraint that the number of transmit antennas has to be greater than or equal to the total number of receive antennas. In this paper, a lattice reduction (LR)-aided flexible coordinated beamforming (LR-FlexCoBF) algorithm is proposed to overcome the dimensionality constraint in overloaded MU-Massive-MIMO systems. A random user selection scheme is integrated with the proposed LR-FlexCoBF to extend its application to MU-Massive-MIMO systems with arbitrary overloading levels. Simulation results show that significant improvements in terms of bit error rate (BER) and sum-rate performances can be achieved by the proposed LR-FlexCoBF precoding algorithm.

## I. INTRODUCTION

The concept of multi-user massive multiple-input multiple-output (MU-Massive-MIMO) systems has been developed recently in [1]-[7] to bring huge improvements in throughput and radiated energy efficiency with inexpensive, low power components. This concept departs from the common understanding of multi-antenna systems and considers a framework in which certain nodes in the network are equipped with antenna arrays featuring a large number of closely spaced radiating elements (several tens to a few hundreds). By exploiting the potential of large spatial dimensions, MU-Massive-MIMO can increase the capacity 10 times or more and simultaneously improve the radiated energy-efficiency [2]. However, the base stations (BSs) are sometimes assumed to have an unlimited number of antennas [4] or the number of BS antennas per user is impractically large [5].

In this work, we focus on the design of downlink precoding algorithms which have dimensionality constraints, also known as overloaded MU-Massive-MIMO systems. As pointed in [8], [9], the application of most precoding algorithms is restricted by the dimensionality constraint that the number of transmit antennas has to be greater than or equal to the total number of receive antennas. Overloaded systems refer to those MIMO system scenarios in which the dimensionality constraint is violated, i.e., the total number of receive antennas exceeds the number of transmit antennas.

To overcome the dimensionality constraint, receive antenna selection and eigenmode selection have been proposed in [10]. In both cases, however, the transmitter and the receiver are not jointly optimized and some signaling techniques are required to indicate the selected receive antennas or eigenmodes. Alternatively, coordinated beamforming (CBF) techniques have been developed to jointly update the transmit-receive beamforming vectors [11]-[15]. However, a study of the convergence behavior in terms of the number of iterations is not considered in [11], and the number of iterations is set manually. The coordinated transmission strategy in [12] only supports a single data stream to each user. To support the transmission of multiple data streams to each user and to reduce the number of iterations, we have developed a flexible coordinated beamforming (FlexCoBF) algorithm in [13], [15].

In order to implement FlexCoBF algorithm, a receive beamforming matrix is employed at each user and is updated with the transmit beamforming matrices iteratively. The receive beamforming matrices may amplify the noise power at the receive side, resulting in a reduced throughput and a degraded bit error rate (BER) performance. To address this performance degradation, a lattice reduction (LR) [16] technique is employed and integrated with the FlexCoBF to further improve the system performances. We term the ratio between the total number of receive antennas and transmit antennas as loading coefficient(LC). In this work, a random user selection scheme is also developed for the proposed LR-FlexCoBF algorithm with arbitrary loading coefficients, which effectively extends the application of FlexCoBF type precoding algorithms to arbitrary overloading scenarios. Moreover, current algorithms for MU-Massive-MIMO systems assume that each user is equipped with a single antenna. However, distributed users equipped with multiple antennas are likely to be common since multiple antennas are already supported in LTE-Advanced [17] and in modern mobile devices [18].

The main contributions of this work are summarized below:

- 1) We study overloaded MU-Massive-MIMO systems. To the best of our knowledge, this is the first time this scenario is discussed for massive MIMO systems.

- 2) A LR-aided FlexCoBF (LR-FlexCoBF) algorithm is proposed to overcome the dimensionality constraint problem in overloaded MU-Massive-MIMO systems.
- 3) A user selection scheme is applied with the FlexCoBF algorithm to adjust the LC, resulting in a controlled sum-rate and BER performance.

This paper is organized as follows. The system model and the LR-aided precoding algorithm are described in Section II and Section III, respectively. The proposed LR-FlexCoBF with random user selection algorithm is described in detail in Section IV. Simulation results and conclusions are presented in Section V and Section VI, respectively.

## II. SYSTEM MODEL

We consider an uncoded MU-Massive-MIMO broadcast system in a single cell environment as illustrated in Fig. 1, equipped with  $M_T$  transmit antennas at the base station (BS),  $K$  users in the system each equipped with  $M_k$  receive antennas, and the total number of receive antennas is  $M_R = \sum_{k=1}^K M_k$ . The combined transmit data streams are denoted as  $\mathbf{s} = [\mathbf{s}_1^T, \mathbf{s}_2^T, \dots, \mathbf{s}_K^T]^T \in \mathbb{C}^{r \times 1}$  with  $\mathbf{s}_k \in \mathbb{C}^{r_k \times 1}$ , where  $r$  is the total number of transmit data streams and  $r_k$  is the number of data streams for user  $k$ . The combined channel matrix is denoted as  $\mathbf{H} = [\mathbf{H}_1^T, \mathbf{H}_2^T, \dots, \mathbf{H}_K^T]^T \in \mathbb{C}^{M_R \times M_T}$  and  $\mathbf{H}_k \in \mathbb{C}^{M_k \times M_T}$  is the  $k$ th user's channel matrix. When channel state information (CSI) is available at the transmit side, precoding techniques can be employed to pre-process the transmit data and to reduce the multi-user interference (MUI) [8]. Due to the large number of antennas at the BS, it is very challenging to acquire CSI in frequency division duplex (FDD) systems. For this reason, massive MIMO systems are likely to operate in the time-division duplex (TDD) model, where the reverse channel is used as an estimate of the forward channel [1]-[7]. We assume a flat fading MIMO channel and the received signal  $\mathbf{y} \in \mathbb{C}^{M_R \times 1}$  is given by

$$\mathbf{y} = \mathbf{H}\mathbf{F}\mathbf{s} + \mathbf{n}, \quad (1)$$

where  $\mathbf{F} = [\mathbf{F}_1 \ \mathbf{F}_2 \ \dots \ \mathbf{F}_K] \in \mathbb{C}^{M_T \times r}$  is the combined precoding matrix and  $\mathbf{n} = [\mathbf{n}_1^T \ \mathbf{n}_2^T \ \dots \ \mathbf{n}_K^T]^T \in \mathbb{C}^{M_R \times 1}$  is the combined Gaussian noise with independent and identically distributed (i.i.d.) entries of zero mean and variance  $\sigma_n^2$ .

## III. LR-AIDED PRECODING ALGORITHM

Lattice reduction (LR) can be considered as a mathematical theory to find a basis with short, nearly orthogonal vectors for a given integer lattice basis [16]. Yao and Wornell [28] first applied the LR algorithm in conjunction with MIMO detection techniques. In prior work [29]-[75] LR-aided MIMO precoding algorithms have been devised and investigated. As shown and studied in these works, the symbol error rate curves of precoding and detection algorithms can approach the maximum diversity order at the receive or transmit side.

Linear precoding can be interpreted as the problem of designing the linear precoding matrix  $\mathbf{F}$  to satisfy an optimization criterion subject to a constraint associated with the transmit power  $E\{\|\beta\mathbf{F}\mathbf{s}\|\} \leq P_s$ , where  $P_s$  is the




Fig. 1. The MU-Massive-MIMO System Model

total transmit power and the factor  $\beta$  is chosen to scale the transmitted power to  $P_s$  [76]. Based on the optimization criterion, linear precoding algorithms can be categorized into zero forcing (ZF) and minimum mean square error (MMSE) based designs [76]. Linear precoding algorithms are attractive due to their simplicity. However, their transmit diversity order is limited as compared to non-linear precoding algorithms such as dirty paper coding (DPC) [77], Tomlinson-Harashima precoding (THP) [78], [79], and vector perturbation (VP) [82], [83]. Although better performance can be achieved by non-linear precoding algorithms, their computational complexity is relatively high in certain scenarios [75].

With the aid of LR techniques, linear precoding techniques can achieve the maximum diversity order while maintaining their simplicity [29]. The most commonly used LR algorithm is the LLL algorithm which was first proposed by Lenstra, Lenstra, and L. Lovász in [16]. By using the LLL algorithm, only the real-valued matrix can be processed which means the channel matrix has to be transformed into equivalent double sized real-valued channel matrix. Thus extra unnecessary complexity could be introduced when the channel has large dimensions. In order to reduce the computational complexity, the complex LLL (CLLL) algorithm was proposed in [84]. The overall complexity of CLLL algorithm is nearly half of the LLL algorithm without sacrificing any performance. Therefore, we employ the CLLL algorithm in this work. A complex lattice is a set of points described by

$$L(\mathbf{H}) = \{\mathbf{H}\mathbf{x} | x_l \in \mathbb{Z} + j\mathbb{Z}\}, \quad (2)$$

where  $\mathbf{H} = [\mathbf{h}_1, \mathbf{h}_2, \dots, \mathbf{h}_{M_T}]$  contains the bases of the lattice  $L(\mathbf{H})$ . The aim of the CLLL algorithm is to find a new basis  $\tilde{\mathbf{H}}$  which is shorter and nearly orthogonal compared to the original matrix  $\mathbf{H}$ . Let us calculate the QR decomposition,  $\mathbf{H} = \mathbf{Q}\mathbf{R}$ , where  $\mathbf{Q}$  is an orthogonal matrix and the upper-triangular matrix  $\mathbf{R}$  is a rotated and reflected representation of  $\mathbf{H}$ . Thus, each column vector  $\mathbf{h}_m$  of  $\mathbf{H}$  is given by [85]

$$\mathbf{h}_m = \sum_{l=1}^m r_{l,m} \mathbf{q}_l, \quad (3)$$

where  $\mathbf{q}_l$  is the  $l$ th column of  $\mathbf{Q}$ . If  $|r_{1,m}|, \dots, |r_{m-1,m}|$  are close to zero, we can say that  $\mathbf{h}_m$  is nearly orthogonal to the space spanned by  $\mathbf{h}_1, \dots, \mathbf{h}_{m-1}$ . Similarly, the QR decomposition of  $\tilde{\mathbf{H}}$  is  $\tilde{\mathbf{H}} = \tilde{\mathbf{Q}}\tilde{\mathbf{R}}$ . Then, the basis for  $L(\mathbf{H})$  is CLLL reduced if both of the following conditions are satisfied

$$|\tilde{r}_{l,m}| \leq \frac{1}{2}|\tilde{r}_{l,l}|, \quad 1 \leq l < m \leq M_T, \quad (4)$$

$$\delta|\tilde{r}_{m-1,m-1}|^2 \leq |\tilde{r}_{m,m}|^2 + |\tilde{r}_{m-1,m}|^2, \quad 2 \leq m \leq M_T, \quad (5)$$

where  $\delta \in (\frac{1}{2}, 1]$  influences the quality of the reduced basis and the computational complexity. We usually set  $\delta = \frac{3}{4}$  to achieve a trade-off between performance and complexity [16].

We perform the LR transformation on the transpose of channel matrix  $\mathbf{H}^T$  [29] as described by

$$\tilde{\mathbf{H}} = \mathbf{T}\mathbf{H} \text{ and } \mathbf{H} = \mathbf{T}^{-1}\tilde{\mathbf{H}}, \quad (6)$$

where  $\mathbf{T}$  is a unimodular matrix with  $\det|\mathbf{T}| = 1$  and all elements of  $\mathbf{T}$  are complex integers, i.e.,  $t_{l,m} \in \mathbb{Z} + j\mathbb{Z}$ . The physical meaning of the constraint  $\det|\mathbf{T}| = 1$  is that the channel energy is still the same after the LR transformation. Following the LR transformation, we employ the linear precoding constraint to get the precoding filter at the transmit side and to process the data streams. The ZF precoding is implemented as

$$\tilde{\mathbf{F}}_{\text{ZF}} = \tilde{\mathbf{H}}^H (\tilde{\mathbf{H}}\tilde{\mathbf{H}}^H)^{-1} = \mathbf{H}^H (\mathbf{H}\mathbf{H}^H)^{-1} \mathbf{T}^{-1}. \quad (7)$$

#### IV. PROPOSED LR-AIDED FLEXCOBF ALGORITHM WITH RANDOM USER SELECTION

For linear or LR-aided precoding techniques to work, it is required that  $M_R \leq M_T$  [8]. When  $M_R > M_T$ , however, precoding techniques cannot perform well simply because the requirement of  $M_R$  data streams is beyond the transmission ability of the systems. For the  $M_R > M_T$  case, we assume that the number of actually transmitted data streams is  $r$  and it should satisfy  $r \leq M_T$ , which means that the maximum number of transmitted data streams cannot exceed the number of transmit antennas  $M_T$ .

In [15], we have developed an iterative coordinated method named FlexCoBF to overcome the dimensionality constraint problem. The receive beamforming matrix  $\mathbf{W}_k \in \mathbb{C}^{r \times M_k}$  is introduced at each user and initialized with random matrices. Then, iterative computations are employed to update the receive beamforming matrix  $\mathbf{W}_k$  and the  $k$ th user's precoding matrix  $\mathbf{F}_k$  jointly to enforce the zero MUI constraint. However, a random user selection scheme is developed in this work to extend the application of FlexCoBF for MU-Massive-MIMO systems with various loading coefficients. Considering the case when  $M_T > K$ , the system can afford one data stream for each user plus extra data streams for  $M_T - K$  users equipped with multiple receive antennas. Assume  $j = M_T - K$ , a random user selection scheme is first implemented to select  $j$  users from a total set of  $K$  users. Then, the remaining  $l = K - j$  users are allocated one data stream by implementing the iterative computations described

above. We define the quantity  $\mathbf{H}_J = [\mathbf{H}_{J_1}^T, \mathbf{H}_{J_2}^T, \dots, \mathbf{H}_{J_j}^T]^T$  is the combined channel matrix of the selected users, and  $\mathbf{H}_L = [\mathbf{H}_{L_1}^T, \mathbf{H}_{L_2}^T, \dots, \mathbf{H}_{L_l}^T]^T$  is the combined channel matrix of the remaining users. Finally, the equivalent channel matrix  $\mathbf{H}_e \in \mathbb{C}^{r \times M_T}$  is obtained as

$$\mathbf{H}_e = \begin{bmatrix} \mathbf{I}_1 & 0 & 0 & 0 & \dots & 0 \\ \vdots & \ddots & \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & \mathbf{I}_j & 0 & \dots & 0 \\ 0 & 0 & 0 & \mathbf{W}_1^H & \dots & 0 \\ \vdots & \vdots & \vdots & \vdots & \ddots & \vdots \\ 0 & 0 & 0 & 0 & \dots & \mathbf{W}_l^H \end{bmatrix} \begin{bmatrix} \mathbf{H}_{J_1} \\ \vdots \\ \mathbf{H}_{J_j} \\ \mathbf{H}_{L_1} \\ \vdots \\ \mathbf{H}_{L_l} \end{bmatrix}. \quad (8)$$

Since the standard lattice reduction algorithm is also restricted by the dimensionality constraint [84], we apply the LR transformation on the equivalent channel matrix  $\mathbf{H}_e$  rather than the channel matrix  $\mathbf{H}$  when  $M_R > M_T$ , i.e.,

$$\tilde{\mathbf{H}}_e = \mathbf{T}_e \mathbf{H}_e, \quad (9)$$

where the quantity  $\tilde{\mathbf{H}}_e \in \mathbb{C}^{r \times M_T}$  is the LR transformed matrix and the transformation matrix  $\mathbf{T}_e \in \mathbb{C}^{r \times r}$  is unimodular ( $|\det(\mathbf{T}_e)| = 1$ ) and all elements of  $\mathbf{T}_e$  are complex integers. The LR transformed matrix  $\tilde{\mathbf{H}}_e$  is a basis of  $\mathbf{H}_e$  in the lattice space. Compared to the original equivalent channel matrix  $\mathbf{H}_e$ , the LR transformed channel matrix  $\tilde{\mathbf{H}}_e$  is closer to orthogonality which can be measured by the orthogonality defect factor defined in [87]. Therefore, improved BER and sum-rate performances can be achieved by the proposed LR-FlexCoBF algorithm.

Assuming that the variable  $p$  represents the iteration index, the proposed LR-FlexCoBF algorithm is performed in the following seven steps:

- 1) Implement the random user selection scheme to select  $J$  users from  $K$ , and get  $\mathbf{H}_J$  and  $\mathbf{H}_L$ , respectively.
- 2) Initialize the iteration index  $p$  to zero and the combined receive beamforming matrix  $\mathbf{W}^{(0)} = \text{diag}\{\mathbf{W}_1^{(0)H}, \mathbf{W}_2^{(0)H}, \dots, \mathbf{W}_l^{(0)H}\}$  to random matrices. Set the constant  $\epsilon$  as the threshold to iteratively enforce the zero MUI constraint for each receiver.
- 3) Set  $p = p + 1$  and compute the equivalent channel matrix  $\mathbf{H}_{L_e}^{(p)}$  as

$$\mathbf{H}_{L_e}^{(p)} = \begin{bmatrix} \mathbf{W}_1^{(p-1)H} \mathbf{H}_{L_1} \\ \mathbf{W}_2^{(p-1)H} \mathbf{H}_{L_2} \\ \vdots \\ \mathbf{W}_K^{(p-1)H} \mathbf{H}_{L_l} \end{bmatrix}.$$

- 4) Apply the ZF constraint based precoding design to the obtained equivalent channel matrix  $\mathbf{H}_{L_e}^{(p)}$  to obtain the transmit beamforming matrices  $\mathbf{F}_k^{(p)}$  for all single data stream users ( $k = 1, \dots, l$ ).

- 5) For the  $p$ th iteration, update  $\mathbf{W}^{(p)}$  jointly with the newly obtained precoding matrix  $\mathbf{F}_{L_e}^{(p)}$  as

$$\mathbf{W}^{(p)} = \mathbf{H} \mathbf{F}_{L_e}^{(p)},$$

where the quantity  $\mathbf{H}$  is the combined channel matrix defined in Section II.

- 6) Track the alterations of the residual MUI after the linear precoding as

$$\text{MUI}(\mathbf{H}_{L_e}^{(p+1)} \mathbf{F}_{L_e}^{(p)}) = \|\text{off}(\mathbf{H}_{L_e}^{(p+1)} \mathbf{F}_{L_e}^{(p)})\|_F^2,$$

where the operation  $\text{off}(\mathbf{B})$  denotes the selection of the off-diagonal elements of the matrix  $\mathbf{B}$ . If the residual MUI is above the threshold  $\epsilon$ , go back to step 2. Otherwise, convergence is achieved and the iterative procedure stops. The final equivalent channel matrix  $\mathbf{H}_e$  and the receive beaforming matrix  $\mathbf{W}_e^{(p)}$  is respectively obtained as  $\mathbf{H}_e = [\mathbf{H}_J^T, \mathbf{H}_{L_e}^{(p)T}]^T$  and  $\mathbf{W}_e^{(p)} = \text{diag}\{\mathbf{I}_J, \mathbf{W}^{(p)}\}$ .

- 7) Perform the LR transformation on the obtained equivalent channel matrix  $\mathbf{H}_e$  to get  $\tilde{\mathbf{H}}_e$  and the transformation matrix  $\mathbf{T}_e$ . Apply the transformation matrix  $\mathbf{T}_e$  to the obtained combined precoding matrix  $\mathbf{F}_e^{(p)} = [\mathbf{F}_1^{(p)}, \mathbf{F}_2^{(p)}, \dots, \mathbf{F}_K^{(p)}]$ , that is,  $\tilde{\mathbf{F}}_e^{(p)} = \mathbf{F}_e^{(p)} \mathbf{T}_e^{-1}$ .

Finally, the received signal for the  $M_R > M_T$  case can be expressed as

$$\mathbf{y} = \mathbf{W}_e^{(p)} \mathbf{H} \tilde{\mathbf{F}}_e^{(p)} \mathbf{s} + \mathbf{n} = \mathbf{W}_e^{(p)} \mathbf{H} \mathbf{F}_e^{(p)} \mathbf{z} + \mathbf{n}, \quad (10)$$

where the quantity  $\mathbf{z} = \mathbf{T}_e^{-1} \mathbf{s}$ . In order to get the estimation of  $\mathbf{z}$ , a proper shifting and scaling work is needed to transform the signal back from the Lattice space [86]. Then, the estimated transmit signal  $\mathbf{s}$  is obtained as  $\hat{\mathbf{s}} = \mathbf{T} \hat{\mathbf{z}}$  with  $\hat{\mathbf{z}}$  is the estimation of  $\mathbf{z}$ .

## V. SIMULATION RESULTS

We consider an overloaded MU-Massive-MIMO system in this section. The quantity  $E_b/N_0$  is defined as  $E_b/N_0 = \frac{M_R P_s}{M_T N \sigma_n^2}$  with  $N$  being the number of information bits transmitted per channel symbol, and the loading coefficient ( $L_C$ ) is defined as  $L_C = \frac{M_R}{M_T}$ . An uncoded QPSK modulation scheme is employed in the simulations. The threshold  $\epsilon$  is set to  $10^{-5}$ , and the maximum number of iterations is restricted to 20. The channel matrix  $\mathbf{H}$  is assumed to be a complex i.i.d. Gaussian matrix with zero mean and unit variance.

The case of  $K = 20$  users each equipped with  $M_k = 2$  receive antennas is first considered in Fig. 2 and Fig. 3. When the loading coefficient  $L_C = 1.0$ , FlexCoBF corresponds to conventional ZF precoding. It is shown in Fig. 2 that the BER performance becomes better with the increase of  $L_C$ . This is because that the inter-stream interference is reduced with the decrease of the equivalent channel matrix dimension. The proposed LR-FlexCoBF has a better performance as compared to the conventional FlexCoBF especially for the heavily overloaded case at high SNRs. The sum-rate performance, which is illustrated in Fig. 3, is inversely proportional to  $L_C$  because more data streams are supported. For example, 40

data streams are supported with  $L_C = 1.0$  while there are only 25 with  $L_C = 1.6$ . It worth noting that a much better sum-rate performance is achieved by the proposed LR-FlexCoBF algorithms.




Fig. 2. BER performance with QPSK,  $K = 20$ ,  $M_k = 2$




Fig. 3. Sum-rate performance,  $K = 20$ ,  $M_k = 2$

The BER and sum-rate performance of  $K = 40$  with  $M_k = 2$  is illustrated in Fig. 4 and Fig. 5, respectively. Similar performances are observed as displayed in Fig. 2 and Fig. 3. It should be noted that for the heavily overloaded case with same  $L_C$ , the BER performance degraded faster than the curve in Fig. 2.

## VI. CONCLUSION

A LR-FlexCoBF algorithm has been proposed to support data transmission in overloaded MU-Massive-MIMO system. By employing a random user selection scheme in conjunction with the proposed LR-FlexCoBF algorithm, MU-Massive-MIMO systems with variety loading coefficients are studied. The proposed LR-FlexCoBF precoding algorithm can achieve a higher diversity order and a higher spatial multiplexing gain as compared to the standard FlexCoBF and other existing techniques.






Fig. 4. BER performance with QPSK,  $K = 40$ ,  $M_k = 2$




Fig. 5. Sum-rate performance,  $K = 40$ ,  $M_k = 2$

## REFERENCES

- [1] T. L. Marzetta, "Noncooperative Cellular Wireless with Unlimited Numbers of Base Station Antennas," *IEEE Trans. Wireless Commun.*, vol. 9, no. 11, pp. 3590-3600, Nov. 2010.
- [2] F. Rusek, D. Persson, B. K. Lau, E. G. Larsson, T. L. Marzetta, O. Edfors, and F. Tufvesson, "Scaling up MIMO: opportunities and challenges with very large arrays," *IEEE Signal Process. Mag.*, vol. 30, no. 1, pp. 40-46, Jan. 2013.
- [3] R. C. de Lamare, "Massive MIMO Systems: Signal Processing Challenges and Future Trends," *URSI Radio Science Bulletin*, Dec. 2013.
- [4] F. Fernandes, A. Ashikhmin, and T. L. Marzetta, "Inter-Cell Interference in Noncooperative TDD Large Scale Antenna Systems," *IEEE J. Sel. Areas Commun.*, vol. 31, no. 2, pp. 192-201, Feb. 2013.
- [5] J. Hoydis, S. ten Brink, and M. Debbah, "Massive MIMO in the UL/DL of Cellular Networks: How Many Antennas Do We Need?," *IEEE J. Sel. Areas Commun.*, vol. 31, no. 2, pp. 160-171, Feb. 2013.
- [6] H. Q. Ngo, E. G. Larsson, and T. L. Marzetta, "Energy and spectral efficiency of very large multiuser MIMO systems," *IEEE Trans. Commun.*, vol. 61, no. 4, pp. 1436-1449, Apr. 2013.
- [7] T. L. Marzetta, "How much training is required for multiuser MIMO?" in *Proc. IEEE Asilomar Conf. on Signals, Systems and Computers*, Pacific Grove, CA, Oct. 2006.
- [8] Q. H. Spencer, C. B. Peel, A. L. Swindlehurst and M. Haardt, "An introduction to the multi-user MIMO downlink," *IEEE Commun. Mag.*, vol. 42, issue: 10, pp. 60-67, Oct. 2004.
- [9] Q. H. Spencer, A. L. Swindlehurst and M. Haardt, "Zero-forcing methods for downlink spatial multiplexing in multiuser MIMO channels," *IEEE Trans. Signal Process.*, vol. 52, no. 2, pp. 461-471, Feb. 2004.
- [10] Z. Shen, R. Chen, J. Andrews, R. Health and B. Evans, "Sum capacity of multiuser MIMO broadcast channels with block diagonalization," *IEEE Trans. Wireless Commun.*, vol. 6, no. 6, pp. 2040-2045, Jun. 2007.
- [11] Z. Zhou, W. Hardjawana and B. Vucetic, "Iterative multiple beamforming algorithm for MIMO broadcast channels," *IEEE Commun. Lett.*, vol. 12, no. 10, pp. 743-745, Oct. 2008.
- [12] C. Chae, D. Marzazese, T. Inoue and R. Health, "Coordinated beamforming for the multiuser MIMO broadcast channel with limited feedforward," *IEEE Trans. Signal Process.*, vol. 56, no. 12, pp. 6044-6056, Dec. 2008.
- [13] B. Song and M. Haardt, "Closed-form coordinated beamforming for multi-user MIMO broadcast channels," in *Proc. Wireless World Research Forum (WWRF)*, Beijing, China, 2009.
- [14] B. Song, F. Roemer and M. Haardt, "Using a new structured joint congruence (STJOCO) transformation of Hermitian matrices for precoding in multi-user MIMO systems," *Proc. IEEE Int. Conf. on Acoustics, Speech, and Signal Processing (ICASSP)*, Dallas, TX, USA, Mar. 2010.
- [15] B. Song, F. Roemer and M. Haardt, "Flexible coordinated beamforming (FlexCoBF) for the downlink of multi-user MIMO systems in single and clustered multiple cells," *Signal Processing*, vol. 93, no. 9, pp. 2462-2473, Sept. 2013.
- [16] A. K. Lenstra, H. W. Lenstra, and L. Lovász, "Factoring polynomials with rational coefficients," *Math. Ann.*, vol. 261, pp. 515-534, 1982.
- [17] *Requirements for Further Advancements for E-UTRA (LTE-Advanced)*, 3GPP TR 36.913 Standard, 2011.
- [18] T. Stevens, "iPhone 5 review," <http://www.engadget.com/2012/09/18/apple-iphone-5-review/>
- [19] P. Clarke, R. C. de Lamare, *Joint Transmit Diversity Optimization and Relay Selection for Multi-relay Cooperative MIMO Systems Using Discrete Stochastic Algorithms*, *IEEE Communications Letters*, vol. 15, p.p. 1035-1037, Oct. 2011.
- [20] P. Clarke and R. C. de Lamare, "Joint iterative power allocation and relay selection for cooperative MIMO systems using discrete stochastic algorithms," *8th International Symposium on Wireless Communication Systems (ISWCS)*, vol., no., pp.432,436, 6-9 Nov. 2011
- [21] P. Clarke and R. C. de Lamare, "Transmit Diversity and Relay Selection Algorithms for Multi-relay Cooperative MIMO Systems", *IEEE Transactions on Vehicular Technology*, vol. 61, no. 3, March 2012, pp. 1084 - 1098.
- [22] R. C. de Lamare and S. Li, "Joint Iterative Power Allocation and Interference Suppression Algorithms for Cooperative DS-CDMA Networks," *2010 IEEE 71st Vehicular Technology Conference (VTC 2010-Spring)*, vol., no., pp.1,5, 16-19 May 2010
- [23] R. C. de Lamare, "Joint Iterative Power Allocation and Interference Suppression Algorithms for Cooperative Spread Spectrum Networks", *Proc. IEEE International Conference on Acoustics, Speech and Signal Processing*, Dallas, USA, March 2010.
- [24] T. Wang, R. C. de Lamare, and P. D. Mitchell, "Low-Complexity Set-Membership Channel Estimation for Cooperative Wireless Sensor Networks," *IEEE Trans. Veh. Technol.*, vol. 60, no. 6, May, 2011.
- [25] S. Li and R. C. de Lamare, "Frequency-domain adaptive detectors for single-carrier frequency-domain equalisation in multiuser direct-sequence ultra-wideband systems based on structured channel estimation and direct adaptation," *IET Communications*, vol.4, no.13, pp. 1636-1650, September 2010.
- [26] R. C. de Lamare, "Joint iterative power allocation and linear interference suppression algorithms for cooperative DS-CDMA networks", *IET Communications*, vol. 6, no. 13, 2012, pp. 1930-1942.
- [27] T. Peng, R. C. de Lamare and A. Schmeink, "Adaptive Distributed Space-Time Coding Based on Adjustable Code Matrices for Cooperative MIMO Relaying Systems", *IEEE Transactions on Communications*, vol. 61, no. 7, July 2013.
- [28] H. Yao and G. Wornell, "Lattice reduction aided detectors for MIMO communication Systems," in *IEEE Proc. Globecom*, Taipei, Taiwan, Nov. 2002.
- [29] C. Windpassinger and R. Fischer, "Low-complexity near-maximum likelihood detection and precoding for MIMO systems using lattice reduction," in *Proc. IEEE Inf. Theory Workshop*, Paris, France, pp. 345-348, Mar. 2003.
- [30] R. C. de Lamare and R. Sampaio-Neto, "Adaptive Reduced-Rank MMSE Filtering with Interpolated FIR Filters and Adaptive Interpolators", *IEEE Sig. Proc. Letters*, vol. 12, no. 3, March, 2005.
- [31] R. C. de Lamare and Raimundo Sampaio-Neto, "Reduced-rank Interference Suppression for DS-CDMA based on Interpolated FIR Filters", *IEEE Communications Letters*, vol. 9, no. 3, March 2005.

- [32] R. C. de Lamare and R. Sampaio-Neto, "Adaptive Interference Suppression for DS-CDMA Systems based on Interpolated FIR Filters with Adaptive Interpolators in Multipath Channels", *IEEE Transactions on Vehicular Technology*, Vol. 56, no. 6, September 2007.
- [33] R. C. de Lamare and R. Sampaio-Neto, "Reduced-Rank Adaptive Filtering Based on Joint Iterative Optimization of Adaptive Filters", *IEEE Sig. Proc. Letters*, Vol. 14, no. 12, December 2007.
- [34] R. C. de Lamare and R. Sampaio-Neto, "Reduced-Rank Space-Time Adaptive Interference Suppression With Joint Iterative Least Squares Algorithms for Spread-Spectrum Systems," *IEEE Transactions on Vehicular Technology*, vol.59, no.3, March 2010, pp.1217-1228.
- [35] R. C. de Lamare and R. Sampaio-Neto, "Adaptive Reduced-Rank MMSE Parameter Estimation based on an Adaptive Diversity Combined Decimation and Interpolation Scheme," *Proc. IEEE International Conference on Acoustics, Speech and Signal Processing*, April 15-20, 2007, vol. 3, pp. III-1317-III-1320.
- [36] R. C. de Lamare and R. Sampaio-Neto, "Adaptive Reduced-Rank Processing Based on Joint and Iterative Interpolation, Decimation, and Filtering," *IEEE Transactions on Signal Processing*, vol. 57, no. 7, July 2009, pp. 2503 - 2514.
- [37] R. C. de Lamare, L. Wang, and R. Fa, "Adaptive reduced-rank LCMV beamforming algorithms based on joint iterative optimization of filters: Design and analysis," *Signal Processing*, vol. 90, no. 2, pp. 640-652, Feb. 2010.
- [38] R. Fa, R. C. de Lamare, and L. Wang, "Reduced-Rank STAP Schemes for Airborne Radar Based on Switched Joint Interpolation, Decimation and Filtering Algorithm," *IEEE Transactions on Signal Processing*, vol.58, no.8, Aug. 2010, pp.4182-4194.
- [39] R.C. de Lamare, R. Sampaio-Neto, M. Haardt, "Blind Adaptive Constrained Constant-Modulus Reduced-Rank Interference Suppression Algorithms Based on Interpolation and Switched Decimation," *IEEE Transactions on Signal Processing*, vol.59, no.2, pp.681-695, Feb. 2011.
- [40] S. Li, R. C. de Lamare, and R. Fa, "Reduced-Rank Linear Interference Suppression for DS-UWB Systems Based on Switched Approximations of Adaptive Basis Functions," *IEEE Transactions on Vehicular Technology*, vol.60, no.2, pp.485-497, Feb. 2011.
- [41] Z. Xu and M.K. Tsatsanis, "Blind adaptive algorithms for minimum variance CDMA receivers," *IEEE Trans. Communications*, vol. 49, No. 1, January 2001.
- [42] R. C. de Lamare and R. Sampaio-Neto, "Low-Complexity Variable Step-Size Mechanisms for Stochastic Gradient Algorithms in Minimum Variance CDMA Receivers", *IEEE Trans. Signal Processing*, vol. 54, pp. 2302 - 2317, June 2006.
- [43] C. Xu, G. Feng and K. S. Kwak, "A Modified Constrained Constant Modulus Approach to Blind Adaptive Multiuser Detection," *IEEE Trans. Communications*, vol. 49, No. 9, 2001.
- [44] Z. Xu and P. Liu, "Code-Constrained Blind Detection of CDMA Signals in Multipath Channels," *IEEE Sig. Proc. Letters*, vol. 9, No. 12, December 2002.
- [45] R. C. de Lamare and R. Sampaio Neto, "Blind Adaptive Code-Constrained Constant Modulus Algorithms for CDMA Interference Suppression in Multipath Channels", *IEEE Communications Letters*, vol 9, no. 4, April, 2005.
- [46] R. C. de Lamare, M. Haardt and R. Sampaio-Neto, "Blind Adaptive Constrained Reduced-Rank Parameter Estimation based on Constant Modulus Design for CDMA Interference Suppression," *IEEE Transactions on Signal Processing*, vol. 56., no. 6, June 2008.
- [47] R. C. de Lamare and P. S. R. Diniz, "Set-membership adaptive algorithms based on time-varying error bounds for CDMA interference suppression," *IEEE Trans. Vehicular Technology*, vol. 58, pp. 644-654, Feb. 2009.
- [48] R. C. de Lamare and P. S. R. Diniz, "Blind Adaptive Interference Suppression Based on Set-Membership Constrained Constant-Modulus Algorithms With Dynamic Bounds," *IEEE Transactions on Signal Processing*, vol.61, no.5, pp.1288-1301, March 2013.
- [49] M. L. Honig and J. S. Goldstein, "Adaptive reduced-rank interference suppression based on the multistage Wiener filter," *IEEE Trans. on Communications*, vol. 50, no. 6, June 2002.
- [50] Y. Sun, V. Tripathi, and M. L. Honig, "Adaptive, Iterative, Reduced-Rank (Turbo) Equalization", *IEEE Trans. on Wireless Communications*, Vol. 4, No. 6, pp. 2789-2800, Nov. 2005.
- [51] Y. Cai and R. C. de Lamare, "Adaptive Linear Minimum BER Reduced-Rank Interference Suppression Algorithms Based on Joint and Iterative Optimization of Filters," *IEEE Communications Letters*, vol.17, no.4, pp.633,636, April 2013.
- [52] R. C. de Lamare and R. Sampaio-Neto, "Reduced-Rank Adaptive Filtering Based on Joint Iterative Optimization of Adaptive Filters," *IEEE Signal Processing Letters*, Vol. 14 No. 12, December 2007, pp. 980 - 983.
- [53] L. Wang, R. C. de Lamare and M. Haardt, "Reduced-rank DOA estimation based on joint iterative subspace recursive optimization and grid search," 2010 IEEE International Conference on Acoustics Speech and Signal Processing (ICASSP), vol., no., pp.2626,2629, 14-19 March 2010
- [54] R. C. de Lamare and R. Sampaio-Neto, "Adaptive Reduced-Rank Processing Based on Joint and Iterative Interpolation, Decimation, and Filtering," *IEEE Transactions on Signal Processing*, vol. 57, no. 7, July 2009, pp. 2503 - 2514.
- [55] R. C. de Lamare and R. Sampaio-Neto, "Reduced-Rank Space-Time Adaptive Interference Suppression With Joint Iterative Least Squares Algorithms for Spread-Spectrum Systems," *IEEE Transactions on Vehicular Technology*, vol.59, no.3, March 2010, pp.1217-1228.
- [56] R. C. de Lamare and R. Sampaio-Neto, "Adaptive reduced-rank equalization algorithms based on alternating optimization design techniques for MIMO systems", *IEEE Transactions on Vehicular Technology*, vol. 60, no. 6, 2482-2494, 2011.
- [57] R. C. de Lamare, R. Sampaio-Neto, "Adaptive MBER decision feedback multiuser receivers in frequency selective fading channels", *IEEE Communications Letters*, vol. 7, no. 2, Feb. 2003, pp. 73 - 75.
- [58] R.C. de Lamare, R. Sampaio-Neto, A. Hjørungnes, "Joint iterative interference cancellation and parameter estimation for cdma systems", *IEEE Communications Letters*, vol. 11, no. 12, December 2007, pp. 916 - 918.
- [59] R. C. de Lamare, R. Sampaio-Neto, *Minimum Mean-Squared Error Iterative Successive Parallel Arbitrated Decision Feedback Detectors for DS-CDMA Systems*, *IEEE Trans. on Commun.*, vol. 56, p.p. 778-789, May 2008.
- [60] A. Rontogiannis, V. Kekatos, and K. Berberidis, "A Square-Root Adaptive V-BLAST Algorithm for Fast Time-Varying MIMO Channels," *IEEE Signal Processing Letters*, Vol. 13, No. 5, pp. 265-268, May 2006.
- [61] R. Fa, R. C. de Lamare, "Multi-Branch Successive Interference Cancellation for MIMO Spatial Multiplexing Systems", *IET Communications*, vol. 5, no. 4, pp. 484 - 494, March 2011.
- [62] P. Li, R. C. de Lamare and R. Fa, "Multiple Feedback Successive Interference Cancellation Detection for Multiuser MIMO Systems," *IEEE Transactions on Wireless Communications*, vol. 10, no. 8, pp. 2434 - 2439, August 2011.
- [63] P. Li and R. C. de Lamare, "Adaptive Decision-Feedback Detection With Constellation Constraints for MIMO Systems", *IEEE Transactions on Vehicular Technology*, vol. 61, no. 2, 853-859, 2012.
- [64] R. C. de Lamare, "Adaptive and Iterative Multi-Branch MMSE Decision Feedback Detection Algorithms for Multi-Antenna Systems", *IEEE Transactions on Wireless Communications*, vol. 14, no. 10, October 2013.
- [65] P. Li and R. C. de Lamare, "Distributed Iterative Detection With Reduced Message Passing for Networked MIMO Cellular Systems," *IEEE Transactions on Vehicular Technology*, vol.63, no.6, pp.2947,2954, July 2014.
- [66] Y. Cai and R. C. de Lamare, "Adaptive Space-Time Decision Feedback Detectors with Multiple Feedback Cancellation", *IEEE Transactions on Vehicular Technology*, vol. 58, no. 8, October 2009, pp. 4129 - 4140.
- [67] J. Liu, R. C. de Lamare, "Low-Latency Reweighted Belief Propagation Decoding for LDPC Codes," *IEEE Communications Letters*, vol. 16, no. 10, pp. 1660-1663, October 2012.
- [68] R. Fischer, C. Windpassinger, "Improved MIMO precoding for decentralized receivers resembling concepts from lattice reduction," in *Proc. IEEE Global Telecommun. Conf.*, San Francisco, CA, USA, pp.1852-1856, Dec. 2003.
- [69] N. Song, R. C. de Lamare, M. Haardt, and M. Wolf, "Adaptive Widely Linear Reduced-Rank Interference Suppression based on the Multi-Stage Wiener Filter," *IEEE Transactions on Signal Processing*, vol. 60, no. 8, 2012.
- [70] C. Windpassinger, R. Fischer and J. Huber, "Lattice reduction aided broadcast precoding," *IEEE Trans. Commun.*, vol. 52, no. 12, pp. 2057-2060, Dec. 2004.

- [71] Y. Cai, R. C. de Lamare and R. Fa, "Switched interleaving techniques with limited feedback for interference mitigation in DS-CDMA systems," *IEEE Trans. Commun.*, vol. 59, no. 7, pp. 1946-1956, July 2011.
- [72] Y. Cai, R. C. de Lamare and D. Le Ruyet, "Transmit Processing Techniques Based on Switched Interleaving and Limited Feedback for Interference Mitigation in Multiantenna MC-CDMA Systems," *IEEE Transactions on Vehicular Technology*, vol.60, no.4, pp.1559,1570, May 2011.
- [73] K. Zu and R. C. de Lamare, "Lattice reduction-aided preprocessing and detection techniques for MU-MIMO in broadcast," in *European Wireless Conf.*, Vienna, Austria, Apr. 2011.
- [74] K. Zu, R. C. de Lamare, "Low-Complexity Lattice Reduction-Aided Regularized Block Diagonalization for MU-MIMO Systems", *IEEE Commun. Lett.*, vol. 16, no. 6, June 2012, pp. 925-928.
- [75] K. Zu, R. C. de Lamare and M. Haardt, "Generalized design of low-complexity block diagonalization type precoding algorithms for multiuser MIMO systems", *IEEE Trans. Commun.*, vol. 61, no. 10, Oct. 2013.
- [76] M. Joham, W. Utschick and J. A. Nossek, "Linear transmit processing in MIMO communications systems," *IEEE Trans. Signal Process.*, vol. 53 no. 8, pp. 2700-2712, Aug. 2005.
- [77] M. Costa, "Writing on dirty paper," *IEEE Trans. Inform. Theory*, vol. 29, no. 3, pp. 439-441, May 1983.
- [78] M. Tomlinson, "New automatic equaliser employing modulo arithmetic," *Electronic Letters*, vol. 7, Mar. 1971.
- [79] H. Harashima and H. Miyakawa, "Matched-transmission technique for channels with intersymbol interference," *IEEE Trans. Commun.*, vol. 20, Aug. 1972.
- [80] K. Zu, R. C. de Lamare and M. Haardt, "Multi-Branch Tomlinson-Harashima Precoding Design for MU-MIMO Systems: Theory and Algorithms," *IEEE Transactions on Communications*, vol.62, no.3, pp.939,951, March 2014.
- [81] L. Zhang, Y. Cai, R. C. de Lamare and M. Zhao, "Robust Multi-branch Tomlinson-Harashima Precoding Design in Amplify-and-Forward MIMO Relay Systems," *IEEE Transactions on Communications*, vol.62, no.10, pp.3476,3490, Oct. 2014.
- [82] B. Hochwald, C. Peel and A. Swindlehurst, "A vector-perturbation technique for near capacity multiantenna multiuser communication - Part II: Perturbation," *IEEE Trans. Commun.*, vol. 53, no. 3, Mar. 2005.
- [83] C. B. Chae, S. Shim and R. W. Heath, "Block diagonalized vector perturbation for multiuser MIMO systems," *IEEE Trans. Wireless Commun.*, vol. 7, no. 11, pp. 4051 - 4057, Nov. 2008.
- [84] Y. H. Gan, C. Ling, and W. H. Mow, "Complex lattice reduction algorithm for low-complexity full-diversity MIMO detection," *IEEE Trans. Sig. Process.*, vol. 57, no. 7, pp. 2701 - 2710, Jul. 2009.
- [85] D. Wübben, R. Böhnke, V. Kühn, and K. Kammeyer, "Near-maximum-likelihood detection of MIMO systems using MMSE-based lattice-reduction," in *ICC'04*, pp. 798-802, Jun. 2004.
- [86] K. Zu and R. C. de Lamare "Switched lattice reduction-aided detection techniques for MIMO systems", *Sensor Signal Processing for Defence Conf.*, London, UK, Sep. 2011.
- [87] M. Taherzadeh, A. Mobasher and A. K. Khandani, "LLL reduction achieves the receiver diversity in MIMO decoding", *IEEE Trans. Inf. Theory*, vol. 53, no. 12, Dec. 2007.
- [88] N. Song, W. U. Alokozai, R. C. de Lamare and M. Haardt, "Adaptive Widely Linear Reduced-Rank Beamforming Based on Joint Iterative Optimization," *IEEE Signal Processing Letters*, vol.21, no.3, pp. 265-269, March 2014.
- [89] R. C. de Lamare and R. Sampaio-Neto, "Sparsity-Aware Adaptive Algorithms Based on Alternating Optimization and Shrinkage," *IEEE Signal Processing Letters*, vol.21, no.2, pp.225,229, Feb. 2014.
- [90] H. Ruan and R. C. de Lamare, "Robust Adaptive Beamforming Using a Low-Complexity Shrinkage-Based Mismatch Estimation Algorithm," *IEEE Signal Processing Letters*, vol.21, no.1, pp.60,64, Jan. 2014.